

DISCONTINUED

grandMA2 light

Art.-No. 120112



The grandMA2 light has 4,096 parameters, 15 motorized executor faders and two touchscreens available. All further features and controls are identical to those on the grandMA2 full-size.

The grandMA2 light is the perfect tool to control all kinds of lighting genres like conventionals, moving lights, LEDs, video and media. It supplies an intuitive and fast control of all connected fixtures and channels. The grandMA2 light can handle an almost infinite number of presets, cues, pages, sequences and effects. It is ideally suited as a standalone console or as a backup device for the grandMA2 full-size. Moreover grandMA series 1-showfiles can be converted to be used with the grandMA2.

All grandMA2 consoles are optionally available as Silent Version with optimised fan for noise-sensitive environments.



DISCONTINUED



Features

- Real-time control for up to 65,536 parameters per session in connection with MA NPU (equivalent to 256 DMX universes)
- 4,096 HTP/LTP parameters
- 6 DMX outputs
- 2 internal TFT wide mode touchscreens (15.4" WXGA)
- 2 external TFT screens can be connected (UXGA, touchscreens accepted)
- 1 internal command screen – multi-touch (9" SVGA)
- 15 motorized executor faders
- Integrated keyboard drawer
- Built-in uninterruptible power supply (UPS)
- 2 etherCON connectors, 5 USB 2.0 connectors
- Motorized monitor wing
- 2 motorized A/B fader (100mm)
- Individually backlit and dimmable silent (clickless) keys

Scope of delivery

Art.-No.	Article	Quantity
120122	MA LED desk light grandMA2, angle plug 90° XLR 4pin, length 27"	2
120132	Dust cover grandMA2 light and ultra-light	1

built-in keyboard

Technical Specifications

Operating voltage/ Supply voltage	120V/230V, 50/60Hz (automatic detection)
Power	350VA
Dimensions	935 x 204 x 652mm / 36.8 x 8 x 25.7inch
Net weight	37kg / 81.6lbs
Output connectors	6 x XLR 5pin (DMX) 2 x DVI (external monitor) 2 x etherCON 1 x MA Link (grandMA2 fader wing) 5 x USB 1 x DIN (MIDI) 2 x XLR 4pin (desklight)
Input connectors	1 x XLR 5pin (DMX) 1 x XLR 3pin (Sound) 1 x XLR 3pin (SMPTE) 1 x DIN (MIDI) 1 x Sub-D 25pol (Analogue Remote) 1 x powerCON

Article

Art.-No.	Article
120112	grandMA2 light

 DISCONTINUED



More product pictures

